

DMR109W

Battery Type:	Lithium-ion
Body only machine:	
Battery Range:	7.2 - 18v
Speakers:	2x76mmØ (8Ω)
Practical Output (7.2v):	0.5W x 2
Practical Output (10.8v):	1.2W x 2
Practical Output (14.4v):	2.2W x 2
Practical Output (18v):	3.5W x 2
Frequency Range DAB:	Band III 5A – 13F
FM Coverage:	87.5 - 108Mhz
Net weight:	4.1 - 4.6kg



- Compatible with 10.8V CXT slide batteries
- Dual power source: AC or Makita batteries.
- Digital tuner
- Flexible antenna can be removed and stored inside the radio.
- Soft grip carry handle swivels 90 degrees
- 2 speaker stereo system.
- Elastomer bumpers protect against rough handling on a jobsite
- Equipped with Micro USB port for software upgrade.
- AUX-IN jack for connecting to external audio source (Connecting cable is not included.)
- AC adaptor jack
- IP64 rated dust and shower-proof construction
- Easy-to-read digital tuner with LCD display