

M18 RC-0 | M18™ jobsite radio/charger

Article: 4933446647



- Built in charger function allows for quick, convenient charging of any M18™ battery or electronic devices via USB port.
- Supplied with auxiliary input cord, 2 x AAA batteries. Milwaukee® batteries sold separately.
- Digital Bluetooth® receiver: play music up to 30 m away from your smartphone, computer, or tablet.
- AC/DC versatility: powered by Milwaukee® M18™ batteries, or 230 V mains supply.
- Exclusive AM/FM tuner with digital processor delivers highest reception accuracy and signal clarity.
- Premium speaker and 40 W amplifier produce rich, full sound.
- Weather sealed auxiliary compartment protects Mp3 players and other audio devices.

	M18 RC-0
Article Number – 240V	4933446647
Battery pack capacity (Ah)	-
Battery type	Li-ion
Charger supplied	-
Dimensions (mm)	300 x 307 x 370
No. of batteries supplied	0
Speaker output (W)	40
Supplied in	-
Voltage (AC) (V)	220 - 240
Voltage (DC) (V)	18
Weight (kg)	7.7